

ENGLISH

# OWNER'S MANUAL

TRIAL CROSS HERO EDITION

# **VEHICLE OVERVIEW**

## **2016 KUBERG TRIAL**

Featuring up to 3 kW of smooth, linear power and instant torque, the Trial is perfect for 5 to 10-year-old riders looking to rip up anything from tracks to trails.

- 1 Throttle
- 2 Handlebar
- 3 Steering column
- 4 Front brake
- 5 Rear brake
- 6 Number plate
- 7 Safety kill-switch
- 8 Battery level indicator
- Tire

- 10 Front fork
- 11 Battery
- 12 Speed & torque control button
- 13 Foot pegs
- 14 Kick stand
- 1 Motor
- 16 Shock absorber
- Tharge port
- 18 Controller





### i NOTE:

Be aware of the motorcycle's chain

Under no circumstances should hands or other body parts be close to a moving motorcycle chain. Riders should wear motorcycle boots without laces, and should not wear any loose clothing that could be caught by the chain.

### **⚠ WARNING: ALWAYS RIDE WITH CHAIN COVER**

The chain cover helps to prevent accidental injuries from the chain. Never ride your motorcycle when the chain cover is not in place. Operating your motorcycle without the chain cover may result in serious injury.

# **SPECIFICATIONS - KUBERG TRIAL**

TOP SPEED	27 KMH (17 MPH)
WEIGHT	33 kg (72 lbs)
POWER	3000 watts, 36 V motor
BATTERIES	3×12 Ah 12 V, sealed lead-acid
CONTROLLER	PWM, 40 amp
INPUT STANDARD	110 V or 220 V
TRANSMISSION	Clutchless one speed

FINAL DRIVE	69T / 10T, chain 219H
FRAME	Steel double cradle tube frame, powder-coated
WHEELBASE	37" (94 cm)
SEAT HEIGHT	20.5/23" (52 cm without seat, 59 cm with seat option)
HANDLEBAR HEIGHT	32.5" (83 cm)
FRONT BRAKE AND REAR BRAKES	Hydraulic Disc Brake system Tektro Auriga
BRAKE DISCS	160 mm diameter
FORKS	Suspension fork Spinner Grind
SHOCK ABSORBER	Spring
TIRES	16" × 2.4" KENDA
WEIGHT	72 lbs (33 kg)
COLORS	White
WIFI	WiFi ready - adapter sold separately
CARRYING CAPACITY	Maximum 220 lbs (100 kg)

### **⚠ WARNING!**

The KUBERG Trial is designed to operate at 36 volts only. Use of any battery voltage other than 24 volts will result in motor failure. KUBERG Inc. considers modifications and/or changes to its electrical components to be a material alteration of its products, thereby cancelling any warranties and/or guarantees in their entirety. Kuberg Inc. will not be responsible for any injuries, and/or death and/or other damage(s) caused by such modifications.